AT320 QuickAdminGuideEng

USER MANUAL

Version 1.0

(Release 08/12/2006)

AT-320 Quick Administrator Guide:

HARD RESET:

Hard-Reset can be performs when you want to reset all the configurations of the phone to the factory default, this is suitable when upgrading the firmware of the phone or when normal configuration can't solve the problem.

1. unplug the power of the phone
2. press "*" on your phone and plug-in the power
3. when the phone display "* Handset Down" on the screen press "#5*5"
4. wait until the phone finish booting process.

SAFE MODE:

Admin can enter the safe-mode when the phone firmware upgrade is not successfully or the phone can't be boot up.

1. unplug the power of the phone
2. press "*" on your phone and plug-in the power

SETUP IP ADDRESS/PHONE CONFIG using phone keypad:

1. Press "SPEAKER" and "1234#"
2. Phone display "Password:" enter the default password "12345678" and "SPEAKER"
3. Phone display "network settings" then press "ok"
4. follow the phone screen step-by-step using

   "set" key when want to change any settings

   "ok" to enter the menu / confirm setting

   "exit" to exit to parent menu

   "Vol+/Vol-" to move in the menu

   "CLEAR" to erase the setting

FIRMWARE UPGRADE using web interface:

1. use web-browser to browse to the IP-Address of the phone
2. enter “12345678” as password
3. click “UPGRADE FIRMWARE”
4. in the “Firmware File Name:” click “Browse” to select the firmware to upgrade
5. click “Update Firmware” to upgrade the firmware.

SETUP THE SPEAKER level:

There are 2 speaker set in the phone

1. Handset
2. Handfree speaker on the phone

Value in the Web Interface can be able to set the speaker level based the two type of the speaker.

“handset in” and “handset out” used to setup handset volume

“speaker in” and “speaker out” used to setup hand-free speaker volume